

Model: 9895B



LED

**Non-contact
Clips**

**CAT
IV/600V**

Features:

- Non-contact detector clips. No metal contact points to promote greater safety.
- Dual functions :
Open phase and phase sequence detection
- Designed for checking a wider range of 3-phase power source from 75V to 1000Vac
- Detects frequency range from 45 to 65 Hz
- LED display lights with buzzer indicator.
- Brightness button feature for better visibility in dimly lit areas or sunlight.
- **Magnetic mounting feature.**
- Meets: EN 61010-1 EN 61326-1
CAT III 1000V/ CAT IV 600V

Scope of Supply:

- 1 pc Safety Rotary Field Indicator 9895B
- 3 pc Safety Crocodile Clamp (Nonmetallic)
- 1 pc Carrying pouch
- 1 pc batteries 9V
- 1 pc Instruction Manual

Safety Rotary Field Indicator Safety Crocodile Clamp (Nonmetallic)

The 9895B Non-Contact Phase Detector provides greater safety from potential electrical shock with its non-contact clips.

Safety is always a priority in electrical work environments. With its non-contact clip design, the 9895B has been designed to ensure greater safety for its users. It eliminates any electrical or short circuit accidents caused by accidental contact between two metal points.

Technical Data:

Voltage Range	75...1000 V
Frequency Range	45-65Hz
Auto-Of	5 min
Low Battery Warning	Power LED flashes at $\leq 7V$
Operating Temperature	-10°C...50°C
Operating Humidity	Max. 80% R.H.
Storage temperature	-20°C...60°C/ Max. 80% R.H.
Power Source	1 x 9 V / IEC 6LR61
Dimensions	128 x 72 x 44 mm
Cable Length	Approx. 800mm
Weight	Approx. 380g (battery included)
Case Dimensions/ Weight	195 x 170 x 75 mm / 650g
Safety Standards	EN 61010-1/ EN 61326-1 / CAT III 1000V/ CAT IV 600V,

